

ACCESSORI

È possibile collegare altri videocitofoni in parallelo (Max 3) a quello in dotazione, come mostrato dallo schema sottostante. Ciascun videocitofono aggiuntivo necessita di un trasformatore di alimentazione Art.850K. L'impostazione standard per i jumper JP1 e JP2 è in posizione "B": nel caso di più videocitofoni collegati in parallelo, per ognuno di essi ad eccezione dell'ultimo (normalmente quello più lontano), spostare i due jumper in posizione "A" al fine di adattare l'impedenza del segnale video. E' possibile collegare un citofono Art. 3111 o un altoparlante supplementare Art. 512A in parallelo a ciascun videocitofono.

ACCESSORIES

Two more videophones can be connected in parallel (max 3) to the one provided, by making the connections described; every additional videophone needs a transformer Art.850K. **The default position for the videophone's jumpers JP1 and JP2 is "B": when you have more videophones in a parallel connection (to adjust the impedance of the video signal), for each one except the last (normally the farthest connected), put the JP1 and JP2 jumpers in position "A".** An intercom Art.3111 or an additional loudspeaker Art.512A can be connected in parallel to every videophone.

